Data sheet



SIMATIC S7-300, CPU 313C-2 PTP Compact CPU with MPI, 16 DI/16 DO, 3 high-speed counters (30 kHz), integrated interface RS485, Integr. power supply 24 V DC, work memory 128 KB, Front connector (1x 40-pole) and Micro Memory Card required

General information	
HW functional status	01
Firmware version	V3.3
Engineering with	
Programming package	STEP 7 as of V5.5 + SP1 or STEP 7 V5.3 + SP2 or higher with HSP 204
Supply voltage	
Rated value (DC)	
• 24 V DC	Yes
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines	Miniature circuit breaker, type C; min. 2 A; miniature circuit
(recommendation)	breaker type B, min. 4 A
Mains buffering	
Mains/voltage failure stored energy time	5 ms
• Repeat rate, min.	1 s
Load voltage L+	
Digital inputs	
— Rated value (DC)	24 V

 Reverse polarity protection 	Yes
Digital outputs	
— Rated value (DC)	24 V
· ·	No
— Reverse polarity protection	NO
Input current	
Current consumption (rated value)	580 mA
Current consumption (in no-load operation), typ.	110 mA
Inrush current, typ.	5 A
l²t	0.7 A ² ·s
Digital inputs	
• from load voltage L+ (without load), max.	80 mA
Digital outputs	
● from load voltage L+, max.	50 mA
Power loss	
Power loss, typ.	9 W
Memory	
Work memory	420 librate
• integrated	128 kbyte
• expandable	No
 Size of retentive memory for retentive data blocks 	64 kbyte
Load memory	
• Plug-in (MMC)	Yes
• Plug-in (MMC), max.	8 Mbyte
 Data management on MMC (after last programming), min. 	10 y
Backup	
• present	Yes; Guaranteed by MMC (maintenance-free)
without battery	Yes; Program and data
CPU processing times	
for bit operations, typ.	0.07 μs
for word operations, typ.	0.15 µs
for fixed point arithmetic, typ.	0.2 μs
for floating point arithmetic, typ.	0.72 μs
CDI I blooks	
CPU-blocks Number of blocks (total)	1 024; (DBs, FCs, FBs); the maximum number of loadable blocks
realiser of stooks (total)	can be reduced by the MMC used.
DB	
• Number, max.	1 024; Number range: 1 to 16000
• Size, max.	64 kbyte
FB	



er range: 0 to 7999 on list
on list
on list
on list
, 34, 35
, 85, 87
22
1:

Counters, timers and their retentivity	
S7 counter	
• Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255
— preset	Z 0 to Z 7
Counting range	
— adjustable	Yes
— lower limit	0
— upper limit	999
IEC counter	
• present	Yes
• Type	SFB
• Number	Unlimited (limited only by RAM capacity)
S7 times	
• Number	256
Retentivity	
— adjustable	Yes
— lower limit	0
— upper limit	255



☼ PNAP

	N
— preset	No retentivity
Time range	
— lower limit	10 ms
— upper limit	9 990 s
IEC timer	
• present	Yes
● Type	SFB
Number	Unlimited (limited only by RAM capacity)
Data areas and their retentivity	
retentive data area in total	all, max. 64 KB
Flag	
Number, max.	256 byte
 Retentivity available 	Yes; MB 0 to MB 255
 Retentivity preset 	MB 0 to MB 15
 Number of clock memories 	8; 1 memory byte
Data blocks	
Retentivity adjustable	Yes; via non-retain property on DB
 Retentivity preset 	Yes
Local data	
• per priority class, max.	32 kbyte; Max. 2048 bytes per block
Address area	
Address area I/O address area	
	1 024 byte
I/O address area	1 024 byte 1 024 byte
I/O address area • Inputs	
I/O address area Inputs Outputs	
I/O address area Inputs Outputs of which distributed	1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs	1 024 byte none
I/O address area Inputs Outputs of which distributed — Inputs — Outputs	1 024 byte none
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image	1 024 byte none none
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs	1 024 byte none none 1 024 byte
I/O address area Inputs Outputs of which distributed Inputs Outputs Process image Inputs Outputs Outputs	none none 1 024 byte 1 024 byte 1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Inputs Inputs Inputs Inputs, adjustable	none none 1 024 byte 1 024 byte 1 024 byte 1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Outputs Outputs Outputs, adjustable Outputs, adjustable	none none 1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Inputs Inputs, adjustable Outputs, adjustable Inputs, default	none none 1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Inputs, adjustable Outputs, adjustable Inputs, default Outputs, default	none none 1 024 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Inputs Outputs Outputs Outputs, adjustable Inputs, default Outputs, default Default addresses of the integrated channels	none none 1 024 byte 1 28 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Inputs, adjustable Outputs, adjustable Inputs, default Outputs, default Default addresses of the integrated channels — Digital inputs	none none 1 024 byte 1 28 byte 128 byte 128 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Outputs Inputs, adjustable Outputs, adjustable Outputs, default Outputs, default Default addresses of the integrated channels — Digital inputs — Digital outputs	none none 1 024 byte 1 28 byte 128 byte 128 byte
I/O address area Inputs Outputs of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Outputs Inputs, adjustable Outputs, adjustable Inputs, default Outputs, default Outputs, default Default addresses of the integrated channels — Digital inputs — Digital outputs Digital channels	none none 1 024 byte 1 128 byte 1 128 byte 1 128 byte
I/O address area Inputs Outputs Of which distributed — Inputs — Outputs Process image Inputs Outputs Outputs Outputs Outputs Inputs, adjustable Outputs, adjustable Outputs, default Outputs, default Default addresses of the integrated channels — Digital inputs — Digital outputs Digital channels Inputs	none none 1 024 byte 1 28 byte 128 byte 128 byte 124.0 to 125.7 124.0 to 125.7



☼ PNAP

— of which central	1 008
Analog channels	
• Inputs	248
— of which central	248
Outputs	248
— of which central	248
Hardware configuration	
Number of expansion units, max.	3
Number of DP masters	
• integrated	none
• via CP	4
Number of operable FMs and CPs (recommended)	
• FM	8
• CP, PtP	8
• CP, LAN	6
Rack	
● Racks, max.	4
Modules per rack, max.	8; In rack 3 max. 7
Time of day	
Clock	
Hardware clock (real-time)	Yes
 retentive and synchronizable 	Yes
Backup time	6 wk; At 40 °C ambient temperature
Deviation per day, max.	10 s; Typ.: 2 s
 Behavior of the clock following POWER-ON 	Clock continues running after POWER OFF
 Behavior of the clock following expiry of backup period 	Clock continues to run with the time at which the power failure occurred
Operating hours counter	
• Number	1
Number/Number range	0
Range of values	0 to 2^31 hours (when using SFC 101)
Granularity	1 h
• retentive	Yes; Must be restarted at each restart
Clock synchronization	
• supported	Yes
• to MPI, master	Yes
• to MPI, slave	Yes
• in AS, master	Yes
• in AS, slave	No
Digital inputs	
Number of digital inputs	16



 of which inputs usable for technological functions 	12
integrated channels (DI)	16
Input characteristic curve in accordance with IEC 61131, type 1	Yes
Number of simultaneously controllable inputs	
horizontal installation	
— up to 40 °C, max.	16
— up to 60 °C, max.	8
vertical installation	
— up to 40 °C, max.	8
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-3 to +5V
● for signal "1"	+15 to +30 V
Input current	
● for signal "1", typ.	8 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes; 0.1 / 0.3 / 3 / 15 ms (You can reconfigure the input delay of the standard inputs during program runtime. Please note that under certain circumstances your newly set filter time may not be effective until the next filter cycle.)
— Rated value	3 ms
for technological functions	
— at "0" to "1", max.	16 µs; Minimum pulse width/minimum pause between pulses at maximum counting frequency
Cable length	
• shielded, max.	1 000 m; 100 m for technological functions
• unshielded, max.	600 m; for technological functions: No
for technological functions	
— shielded, max.	100 m; at maximum count frequency
— unshielded, max.	not allowed
Digital outputs	
Number of digital outputs	16
 of which high-speed outputs 	4; Notice: You cannot connect the fast outputs of your CPU in parallel
integrated channels (DO)	16
Short-circuit protection	Yes; Clocked electronically
 Response threshold, typ. 	1 A
Limitation of inductive shutdown voltage to	L+ (-48 V)
Controlling a digital input	Yes
Switching capacity of the outputs	



• on lamp load, max.	5 W
Load resistance range	
• lower limit	48 Ω
• upper limit	4 kΩ
Output voltage	
● for signal "1", min.	L+ (-0.8 V)
Output current	
● for signal "1" rated value	500 mA
• for signal "1" permissible range, min.	5 mA
• for signal "1" permissible range, max.	0.6 A
for signal "1" minimum load current	5 mA
• for signal "0" residual current, max.	0.5 mA
Parallel switching of two outputs	
• for uprating	No
 for redundant control of a load 	Yes
Switching frequency	
with resistive load, max.	100 Hz
 with inductive load, max. 	0.5 Hz
● on lamp load, max.	100 Hz
• of the pulse outputs, with resistive load, max.	2.5 kHz
Total current of the outputs (per group)	
horizontal installation	
— up to 40 °C, max.	3 A
— up to 60 °C, max.	2 A
vertical installation	
— up to 40 °C, max.	2 A
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Analog inputs	
Number of analog inputs	0
integrated channels (AI)	0
Analog outputs	
Number of analog outputs	0
integrated channels (AO)	0
Encoder	
Connectable encoders	
• 2-wire sensor	Yes
 permissible quiescent current (2-wire sensor), max. 	1.5 mA
3011301), 111ax.	



Ö PNAP

 Interfaces	
Number of industrial Ethernet interfaces	0
Number of PROFINET interfaces	0
Number of RS 485 interfaces	1; MPI
Number of RS 422 interfaces	1; RS 422 / 485 combined
Point-to-point connection	1, NO 422 / 465 COMBINED
Cable length, max.	1 200 m
-	1 200 111
Integrated protocol driver	Yes
— 3964 (R)	
— ASCII	Yes
— RK 512	No
Transmission rate, RS 422/485	
— with 3964 (R) protocol, max.	19.2 kbit/s; 38.4 kbit/s half duplex; 19.2 kbit/s full duplex
— with ASCII protocol, max.	19.2 kbit/s; 38.4 kbit/s half duplex; 19.2 kbit/s full duplex
1. Interface	
Interface type	Integrated RS 485 interface
Physics	RS 485
Isolated	No
Power supply to interface (15 to 30 V DC), max.	200 mA
Protocols	
• MPI	Yes
 PROFIBUS DP master 	No
 PROFIBUS DP slave 	No
Point-to-point connection	No
MPI	
Transmission rate, max.	187.5 kbit/s
Services	
— PG/OP communication	Yes
— Routing	No
Global data communication	Yes
— S7 basic communication	Yes
— S7 communication	Yes; Only server, configured on one side
— S7 communication, as client	No; but via CP and loadable FB
— S7 communication, as server	Yes
or communication, as server	
2. Interface	
Interface type	Integrated RS 422/ 485 interface
Physics	RS 422 / 485 (X.27)
Isolated	Yes
Power supply to interface (15 to 30 V DC), max.	No
Protocols	
• MPI	No



 PROFINET IO Controller 	No
PROFINET IO Device	No
• PROFINET CBA	No
 PROFIBUS DP master 	No
PROFIBUS DP slave	No
Point-to-point connection	
Transmission rate, max.	19.2 kbit/s; 38.4 kbit/s half duplex; 19.2 kbit/s full duplex
 Interface controllable from the user program 	Yes
 Interface can trigger alarm/interrupt in the user 	Yes; Message on break - identification
program	
Communication functions	
PG/OP communication	Yes
Data record routing	No
Global data communication	
• supported	Yes
Number of GD loops, max.	8
Number of GD packets, max.	8
 Number of GD packets, transmitter, max. 	8
 Number of GD packets, receiver, max. 	8
Size of GD packets, max.	22 byte
 Size of GD packet (of which consistent), max. 	22 byte
S7 basic communication	
• supported	Yes; Server
User data per job, max.	76 byte
 User data per job (of which consistent), max. 	76 byte; 76 bytes (with X_SEND or X_RCV); 64 bytes (with X_PUT or X_GET as server)
S7 communication	
• supported	Yes
• as server	Yes
• as client	Yes; Via CP and loadable FB
 User data per job, max. 	180 byte; With PUT/GET
• User data per job (of which consistent), max.	240 byte; as server
S5 compatible communication	
• supported	Yes; via CP and loadable FC
Number of connections	
• overall	8
 usable for PG communication 	7

6ES7313-6BG04-0AB0
Page 9/12


- reserved for PG communication

— reserved for OP communication

• usable for OP communication

— adjustable for PG communication, min.

— adjustable for PG communication, max.



1 1

7

7

1

PNAP

— adjustable for OP communication, min.	1
— adjustable for OP communication, max.	7
 usable for S7 basic communication 	4
— reserved for S7 basic communication	0
— adjustable for S7 basic communication,	0
min.	
 adjustable for S7 basic communication, 	4
max.	

S7 message functions	
Number of login stations for message functions, max.	8; Depending on the configured connections for PG/OP and S7
	basic communication
Process diagnostic messages	Yes
simultaneously active Alarm-S blocks, max.	300
Test commissioning functions	
Status block	Yes; Up to 2 simultaneously
Single step	Yes
Number of breakpoints	4
Status/control	
Status/control variable	Yes
Variables	Inputs, outputs, memory bits, DB, times, counters
	30
Number of variables, max.	
of which status variables, max.	30
of which control variables, max.	14
Forcing	
• Forcing	Yes
• Forcing, variables	Inputs, outputs

Forcing, variables	Inputs, outputs
 Number of variables, max. 	10
Diagnostic buffer	
• present	Yes
 Number of entries, max. 	500
— adjustable	No
of which powerfail-proof	100; Only the last 100 entries are retained
 Number of entries readable in RUN, max. 	499
— adjustable	Yes; From 10 to 499
— preset	10
Service data	
• can be read out	Yes

Interrupts/diagnostics/status information	
Diagnostics indication LED	
Status indicator digital input (green)	Yes
 Status indicator digital output (green) 	Yes



tegrated Functions	
Number of counters	3; See "Technological Functions" manual
Counting frequency (counter) max.	30 kHz
Frequency measurement	Yes
Number of frequency meters	3; up to 30 kHz (see "Technological Functions" manual)
controlled positioning	No
integrated function blocks (closed-loop control)	Yes; PID controller (see "Technological Functions" manual)
PID controller	Yes
Number of pulse outputs	3; Pulse width modulation up to 2.5 kHz (see "Technological Functions" Manual)
Limit frequency (pulse)	2.5 kHz
otential separation	
Potential separation digital inputs	
Potential separation digital inputs	Yes
• between the channels	No
• between the channels and backplane bus	Yes
Potential separation digital outputs	
Potential separation digital outputs	Yes
• between the channels	Yes
• between the channels, in groups of	8
• between the channels and backplane bus	Yes
olation	
Isolation tested with	600 V DC
mbient conditions	
Ambient temperature during operation	
9 - 1 - 1 - 1 - 1 - 1 - 1	
• min.	0 °C
	0 °C
• min. • max.	
• min.	
min. max. onfiguration	
min.max. onfiguration Configuration software	60 °C Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or
min. max. onfiguration Configuration software STEP 7 STEP 7 Lite	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
min. max. onfiguration Configuration software STEP 7 STEP 7 Lite	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203
 min. max. Onfiguration Configuration software STEP 7 STEP 7 Lite Programming	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No
 min. max. Onfiguration Configuration software STEP 7 STEP 7 Lite Programming Command set 	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No see instruction list
 min. max. Onfiguration Configuration software STEP 7 STEP 7 Lite Programming Command set Nesting levels System functions (SFC) 	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No see instruction list 8
min. max. configuration Configuration software STEP 7 STEP 7 Lite Programming Command set Nesting levels System functions (SFC) System function blocks (SFB)	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No see instruction list 8 see instruction list
 min. max. Onfiguration Configuration software STEP 7 STEP 7 Lite Programming Command set Nesting levels System functions (SFC) System function blocks (SFB) Programming language	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No see instruction list 8 see instruction list
min. max. configuration Configuration software STEP 7 STEP 7 Lite Programming Command set Nesting levels System functions (SFC) System function blocks (SFB)	Yes; STEP 7 V5.5 + SP1 or higher or STEP 7 V5.3 + SP2 or higher with HSP 203 No see instruction list 8 see instruction list see instruction list



last modified: 10/09/2020

