

SIMATIC S7-300, Counter module FM 350-1 for S7-300, Counter functions up to 500 kHz 1 channel for connection of 5 V and 24 V incremental encoders Isochronous mode; Measuring range types incl. configuration package on CD



Supply voltage	
Auxiliary voltage 1L+, load voltage 2L+	
<ul style="list-style-type: none"> Rated value (DC) 	24 V
<ul style="list-style-type: none"> permissible range, lower limit (DC) 	20.4 V; Dynamic 18.5 V
<ul style="list-style-type: none"> permissible range, upper limit (DC) 	28.8 V; dynamic 30.2 V
Input current	
from load voltage 1L+ (without load), max.	40 mA
from backplane bus 5 V DC, max.	160 mA
Encoder supply	
5 V encoder supply	
<ul style="list-style-type: none"> 5 V 	Yes; 5.2 V \pm 2 %
<ul style="list-style-type: none"> Output current, max. 	300 mA
24 V encoder supply	
<ul style="list-style-type: none"> 24 V 	Yes; 1L+ (-3 V)
<ul style="list-style-type: none"> Output current, max. 	400 mA
Power loss	
Power loss, typ.	4.5 W

Digital inputs	
Number of digital inputs	3
Functions	1 for gate start, 1 for gate stop, 1 for setting the counter
Input voltage	
<ul style="list-style-type: none"> for signal "0" for signal "1" 	-28.8 ... +5V +11 to +28.8V
Input current	
<ul style="list-style-type: none"> for signal "1", typ. 	9 mA
Digital outputs	
Number of digital outputs	2
Short-circuit protection	Yes; Clocked electronically
Limitation of inductive shutdown voltage to	2L+ (-39 V)
Output voltage	
<ul style="list-style-type: none"> for signal "0", max. for signal "1", min. 	3 V 2L+ (-1,5 V)
Output current	
<ul style="list-style-type: none"> for signal "1" rated value for signal "1" permissible range for 0 to 60 °C, min. for signal "1" permissible range for 0 to 60 °C, max. 	0.5 A 5 mA 0.6 A
Output delay with resistive load	
<ul style="list-style-type: none"> "0" to "1", max. 	300 µs
Encoder	
Connectable encoders	
<ul style="list-style-type: none"> Incremental encoder (symmetrical) Incremental encoder (asymmetrical) 24 V initiator 24 V directional element 	Yes; With 2 pulse trains offset by 90° Yes Yes Yes; 1 pulse train, 1 direction level
Counter	
Number of counter inputs	1; 32 bit or ±31 bit
Counter input 5 V	
<ul style="list-style-type: none"> Type Terminating resistor Differential input voltage Counting frequency, max. 	RS 422 220 Ω 1,3 V 500 kHz
Counter input 24 V	
<ul style="list-style-type: none"> Input voltage for signal "0" Input voltage for signal "1" Input current for signal "1", typ. Counting frequency, max. 	-28.8 ... +5V +11 to +28.8V 9 mA 200 kHz

• Minimum pulse width 2.5 μ s

Potential separation

Potential separation digital inputs

• between the channels and backplane bus Yes; Optocoupler

Potential separation digital outputs

• between the channels and backplane bus Yes; Optocoupler

Potential separation counter

• between the channels and backplane bus Yes; Optocoupler

Isolation

Isolation tested with 500 V

Connection method

required front connector 1x 20-pin

Dimensions

Width 40 mm

Height 125 mm

Depth 120 mm

Weights

Weight, approx. 250 g

last modified: 10/13/2020