

SIMATIC S7, IF964-DP Interface module DP master for S7-400



### Input current

Current consumption, max.

150 mA; Current consumption from S7-400 bus: The module uses no current at 24 V, it provides this voltage only at the DP interface. Total current consumption of the components connected to the DP interface, but maximum 150 mA. Current carrying capacity of the isolated 5 V (P5ext) maximum 90 mA, current carrying capacity of the 24 V maximum 150 mA.

### Power loss

Power loss, typ.

1 W

### Interfaces

PROFIBUS DP

- Cable length, max.

1 200 m; At 9.6 kbit/s: max. 1 200 m; at 12 Mbit/s: max. 100 m

### 1. Interface

Isolated

Yes

### Protocols

- PROFIBUS DP master
- PROFIBUS DP slave

Yes; Default setting

Yes

PROFIBUS DP master

• Transmission rate, max.	12 Mbit/s
• Number of DP slaves, max.	125; depending on the CPU used
<b>Services</b>	
— PG/OP communication	Yes
— Equidistance	Yes
— SYNC/FREEZE	Yes
— Direct data exchange (slave-to-slave communication)	Yes
<b>Address area</b>	
— Inputs, max.	device-dependent
— Outputs, max.	device-dependent
<b>User data per DP slave</b>	
— Inputs, max.	244 byte
— Outputs, max.	244 byte
<b>Communication functions</b>	
<b>Number of connections</b>	
• overall	device-dependent
<b>Dimensions</b>	
Width	26 mm
Height	54 mm
Depth	130 mm
<b>Weights</b>	
Weight, approx.	65 g

**last modified:** 10/16/2020