

MLFB-Ordering data

6SL3210-1KE21-3UF1



Figure similar

Client order no. :	
Order no. :	
Offer no. :	

Remarks :				
Rated data		General tech. specifications		
Input		Power factor λ	0.70 0.85	
Number of phases	3 AC	Offset factor cos φ	0.95	
Line voltage	380 480 V +10 % -20 %	Efficiency η	0.97	
Line frequency	47 63 Hz	Sound pressure level (1m)	63 dB	
Rated current (LO)	16.50 A	Power loss	0.18 kW	
Rated current (HO)	12.80 A	Filter class (integrated)	Unfiltered	
Output		Ambien	t conditions	
Number of phases	3 AC	Ambien	it conditions	
Rated voltage	400 V	Cooling	Air cooling using an integrated fan	
Rated power IEC 400V (LO)	5.50 kW		0.000 31 (0.040 (31)	
Rated power NEC 480V (LO)	7.50 hp	Cooling air requirement	0.009 m³/s (0.318 ft³/s)	
Rated power IEC 400V (HO)	4.00 kW	Installation altitude	1000 m (3280.84 ft)	
Rated power NEC 480V (HO)	5.00 hp	Ambient temperature		
Rated current (IN)	13.00 A	Operation	-10 40 °C (14 104 °F)	
Rated current (LO)	12.50 A	Transport	-40 70 °C (-40 158 °F)	
Rated current (HO)	8.80 A	Storage	-40 70 °C (-40 158 °F)	
Max. output current	17.60 A	Relative humidity		
Pulse frequency	4 kHz	Max. operation	95 % At 40 °C (104 °F), condensation and icing not permissible	
Output frequency for vector control	0 240 Hz			
	S 2 . S 2	Closed-loop control techniques		
Output frequency for V/f control	0 550 Hz	V/f linear / square-law / parameterizable Yes		
		V/f with flux current control (FC	C) Yes	
Overload capability		V/f ECO linear / square-law	Yes	
Low Overload (LO)		Sensorless vector control	Yes	

Vector control, with sensor

Encoderless torque control

Torque control, with encoder

Item no.: Consignment no. :

Project :

300 s cycle time

300 s cycle time

High Overload (HO)

150 % base load current IL for 3 s, followed by 110 % base load current IL for 57 s in a

200 % base load current IH for 3 s, followed by 150 % base load current IH for 57 s in a

No

No

No



MLFB-Ordering data

6SL3210-1KE21-3UF1



		1	Figure similar
Mechanical data		Communication	
Degree of protection	IP20 / UL open type	Communication	PROFINET, EtherNet/IP
Size	FSB	Connections	
Net weight	2.30 kg (5.07 lb)	Signal cable	
Width	100 mm (3.94 in)	Conductor cross-section	0.15 1.50 mm² (AWG 24 AWG 16)
Height	196 mm (7.72 in)	Line side	
Depth	208 mm (8.19 in)	Version	Plug-in screw terminals
Inputs / out	Inputs / outputs		4.00 6.00 mm² (AWG 12 AWG 10)
Standard digital inputs		Motor end	
Number	6	Version	Plug-in screw terminals
Switching level: 0→1	11 V	Conductor cross-section	4.00 6.00 mm² (AWG 12 AWG 10)
Switching level: 1→0	5 V	DC link (for braking resistor)	
Max. inrush current	15 mA	Version	Plug-in screw terminals
Fail-safe digital inputs		Conductor cross-section	4.00 6.00 mm² (AWG 12 AWG 10)
Number	1	Line length, max.	15 m (49.21 ft)
Digital outputs		-	
Number as relay changeover contact	1	PE connection Max. motor cable length	On housing with M4 screw
	·	Max. Motor cable length	
Output (resistive load)	DC 30 V, 0.5 A	Shielded	50 m (164.04 ft)
Number as transistor	1	Unshielded	150 m (492.13 ft)
Output (resistive load)	DC 30 V, 0.5 A	Standards	
Analog / digital inputs		Compliance with standards	UL, cUL, CE, C-Tick (RCM)
Number	1 (Differential input)		
Resolution	10 bit	CE marking	EMC Directive 2004/108/EC, Low-Voltage Directive 2006/95/EC

Switching threshold as digital input

0→1	4 V
1→0	1.6 V

Analog outputs

Number	1 (Non-isolated output)

PTC/ KTY interface

1 motor temperature sensor input, sensors that can be connected: PTC, KTY and Thermo-Click, accuracy $\pm 5~^\circ\text{C}$



MLFB-Ordering data


6SL3210-1KE21-3UF1



Figure similar

Converter losses to EN 50598-2*

Efficiency class	IE2
Comparison with the reference converter (90% / 100%)	-66.06 %



The percentage values show the losses in relation to the rated apparent power of the converter.

The diagram shows the losses for the points (as per standard EN 50598) of the relative torque generating current (I) over the relative motor stator frequency(f). The values are valid for the basic version of the converter without options/components.

*converted values

