

MLFB-Ordering data

6SL3210-5BB17-5AV0



Figure similar

Client order no. : Order no.: Offer no. :

Remarks :

Item no.: Consignment no.:

Project :

| Rated data | | General tech. specifications | |
|--------------------|-----------------------|------------------------------|--------------------------------------|
| nput | | Power factor λ | 0.72 |
| Number of phases | 1 AC | Offset factor cos φ | 0.95 |
| Line voltage | 200 240 V -10 % +10 % | Efficiency η | 0.98 |
| Line frequency | 47 63 Hz | Filter class (integrated) | Class A |
| utput | | Ambient conditions | |
| Number of phases | 3 AC | Cooling | convection cooling |
| Rated voltage | 230 V | Installation altitude | 1000 m (3281 ft) |
| Rated power (HO) | 0.75 kW / 0.75 hp | | 1000 III (3201 II) |
| Rated power (LO) | 0.75 kW / 0.75 hp | Ambient temperature | 10 (0.00 (14 140.05) |
| Rated current (HO) | 3.90 A | Operation | -10 60 °C (14 140 °F) |
| Rated current (LO) | 3.90 A | Storage Relative humidity | -40 70 °C (-40 158 °F) |
| | | Max. operation | 95 % |
| Pulse frequency | 8.00 kHz | Communication | |
| Output frequency | 0 550 Hz | Communication | USS, Modbus RTU |
| | | Standards | |
| | | Compliance with standards | CE, cULus, C-Tick (RCM), KC |
| | | CE marking | EN 61800-5-1 /EN 60204-1 and 61800-3 |

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s





MLFB-Ordering data

Number

6SL3210-5BB17-5AV0



Figure similar

| Mecha | anical data | Connections Max. motor cable length | |
|-------------------------------|---|--------------------------------------|---------------|
| Mounting position | Wall mounting / side-by-side mounting | | |
| | | Shielded | 10 m (33 ft) |
| Degree of protection | P20 / UL open type | Unshielded | 50 m (164 ft) |
| Size | FSA | | |
| Net weight | 1.10 kg (2.43 lb) | | |
| Width | 90.0 mm (3.54 in) | | |
| Height | 150.0 mm (5.91 in) | | |
| Depth | 145.5 mm (5.73 in) | | |
| Input | s / outputs | | |
| tandard digital inputs | | _ | |
| Number | 4 | | |
| igital outputs | | | |
| Number as relay changeover co | ontact 1 | | |
| Number as transistor | 1 | | |
| nalog inputs | | | |
| Number | 2 (Can be used as additional digital input) | | |
| Analog outputs | | | |

