

MLFB-Ordering data

6SL3210-5BE31-5CV0



Figure similar

Client order no. :
Order no. :
Offer no. :
Remarks :

Item no. :
Consignment no. :
Project :

Rated	data	General tecl	General tech. specifications		
Input		Power factor λ	0.72		
Number of phases	3 AC	Offset factor $\cos \phi$	0.95		
Line voltage	380 480 V -15 % +10 %	Efficiency η	0.98		
Line frequency	47 63 Hz	Filter class (integrated)	Class A		
Output		Ambient conditions			
Number of phases	3 AC	Cooling	External fan		
Rated voltage	400 V	Installation altitude	1000 m (3281 ft)		
Rated power (HO)	15.00 kW / 20.00 hp	Ambient temperature			
Rated power (LO)	15.00 kW / 20.00 hp				
Rated current (HO)	31.00 A	Operation	-10 60 °C (14 140 °F)		
Rated current (LO)	31.00 A	Storage	-40 70 °C (-40 158 °F)		
Rated current (HO) at 480V	31.00 A	Relative humidity			
Rated current (LO) at 480V	31.00 A	Max. operation	95 %		
Pulse frequency	4.00 kHz	Communication			
Output frequency	0 550 Hz	Communication	USS, Modbus RTU		
		Standards			
		Compliance with standards	CE, cULus, C-Tick (RCM), KC		
		CE marking	EN 61800-5-1 /EN 60204-1 and EN 61800-3		

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s

Technical data are subject to change! There may be discrepancies between calculated and rating plate values.





MLFB-Ordering data

6SL3210-5BE31-5CV0



Figure similar

Mechanical data		Connections			
Mounting position	Through-hole mounting / wall mounting / side-by-side mounting		Max. motor cable length		
			Shielded		25 m (82 ft)
Degree of protection	P20 / UL c	pen type	Unshielded		50 m (164 ft)
Size F	SD				
Net weight 4	4.30 kg (9.48 lb)				
Width 2	240.0 mm (9.45 in)				
Height 2	206.5 mm (8.13 in)				
Depth 1	172.5 mm	(6.79 in)			
Inputs / outputs					
Standard digital inputs			J		
Number		4			
Digital outputs					
Number as relay changeover co	ntact	1			
Number as transistor		1			
Analog inputs					
Number		2 (Can be used as additional digital input)			
Analog outputs					
Number		1			

