
## **SIEMENS**

## **Data sheet**

accessories circuit breaker 3WL aux.switch block 2NO +2NC



Model						
product brand name			SENTRON			
product designation			Auxiliary contacts for switch position			
design of the product			Accessories			
General technical data						
degree of pollution			3			
Voltage						
surge voltage resistance / rated value			4 kV			
Supply voltage						
operating voltage						
<ul><li>at AC / at 50 Hz / rated value / maximum</li></ul>			500 V			
<ul><li>at DC / rated value / maximum</li></ul>			500 V			
Current						
operational current						
• at AC-12 / at 110 V / rated value			10 A			
<ul><li>at AC-12 / at 24 V / rated value</li></ul>			10 A			
<ul><li>at AC-12 / at 48 V / rated value</li></ul>			10 A			
<ul><li>at AC-12 / at 400 V / rated value</li></ul>			10 A			
<ul><li>at AC-12 / at 230 V / rated value</li></ul>			10 A			
<ul><li>at AC-15 / at 24 V / rated value</li></ul>			4 A			
<ul><li>at AC-15 / at 48 V / rated value</li></ul>			4 A			
<ul><li>at AC-15 / at 110 V / rated value</li></ul>			4 A			
• at AC-15 / at 230 V / rated value			4 A			
<ul><li>at AC-15 / at 400 V / rated value</li></ul>			3 A			
• at DC-12 / at 230 V / rated value			1 A			
• at DC-13 / at 220 V / rated value			0.4 A			
• at DC-12 / at 110 V / rated value			3.5 A			
• at DC-12 / at 48 V / rated value			8 A			
• at DC-13 / at 110 V / rated value			1.2 A			
• at DC-13 / at 48 V / rated value			4 A			
at DC-12 / at 24 V / rated value			10 A			
• at DC-13 / at 24 V / rated value			8 A			
General Product Approval	EMC	Declaration of Conformity	of	Test Certificates	other	







**Miscellaneous** 

Manufacturer Declaration

**Environmental Confirmations** 

other

Miscellaneous

## Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

http://www.siemens.com/lowvoltage/catalogs

Industry Mall (Online ordering system)

https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3WL9111-0AG01-0AA0

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

https://support.industry.siemens.com/cs/ww/en/ps/3WL9111-0AG01-0AA0

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

http://www.automation.siemens.com/bilddb/cax\_en.aspx?mlfb=3WL9111-0AG01-0AA0

**CAx-Online-Generator** 

http://www.siemens.com/cax

**Tender specifications** 

http://www.siemens.com/specifications



